





$$\sigma = \frac{T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{dv} t},$$













$$\sigma = \sqrt{\sigma_{\text{on}}^2 + \sigma_{\text{off}}^2} = \frac{T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{d\nu} t_{\text{sig}}} \quad \text{with} \quad t_{\text{sig}} = \frac{t_{\text{on}} t_{\text{off}}}{t_{\text{on}} + t_{\text{off}}},$$













$$T_{\text{sys}} = \frac{(1 + G_{\text{im}}) \exp \{ \tau_s A \}}{F_{\text{eff}}} [F_{\text{eff}} T_{\text{atm}} (1 - \exp \{ -\tau_s A \}) + (1 - F_{\text{eff}}) T_{\text{cab}} + T_{\text{rec}}],$$







Adrianus























pop1



$$\sigma = \frac{T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{dv} \, n_{\text{pol}} \, t_{\text{sig}}} \quad \text{with} \quad t_{\text{sig}} = \frac{t_{\text{on}} \, t_{\text{off}}}{t_{\text{on}} + t_{\text{off}}}.$$



$$t_{sig} = \frac{t_{on}}{2} = \frac{t_{off}}{2} = \frac{t_{onoff}}{2},$$



$$\sigma_{\text{fsw}} = \frac{\sqrt{2} T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{dv} \, \eta_{\text{pol}} \, \eta_{\text{tel}} \, t_{\text{tel}}}.$$

$$t_{on} = t_{off} = \frac{t_{onoff}}{2},$$

$$t_{sig} = \frac{t_{on}}{2} = \frac{t_{off}}{2} = \frac{t_{onoff}}{4},$$

$$\sigma_{\text{psw}} = \frac{2 T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{d\nu} \, \eta_{\text{pol}} \, \eta_{\text{tel}} \, t_{\text{tel}}} .$$



A pixelated, grayscale image of the word "Amp" in a stylized, blocky font. The letters are composed of various shades of gray and black pixels, giving it a retro, digital appearance. The 'A' is on the left, followed by 'm', 'p', and 'p'. The image is set against a plain white background.

1990





$$A_{\text{beam}} = \frac{n_{\text{grid}} \pi \theta^2}{4 \ln(2)}$$





$$n_{grid} = 1 + \frac{1}{9} \approx 1.11.$$



$$n_{\text{beam}} = \frac{A_{\text{map}}}{A_{\text{beam}}}.$$

beard

00

beard



beach  
side

$$t_{\text{sig}}^{\text{beam}} = \frac{t_{\text{on}}^{\text{beam}} t_{\text{off}}^{\text{beam}}}{t_{\text{on}}^{\text{beam}} + t_{\text{off}}^{\text{beam}}}$$








WIRTSCHAFTS  
UNIVERSITÄT  
WIEN VIENNA  
UNIVERSITY OF  
ECONOMICS  
AND BUSINESS











$$\Delta \theta = \frac{\theta}{2.5} \cdot$$



$$t_{\text{beam on}} = t_{\text{beam off}} = \frac{t_{\text{onoff}}}{n_{\text{beam}}} ;$$

$$t_{\text{sig}}^{\text{beam}} = \frac{t_{\text{on}}^{\text{beam}}}{2} = \frac{t_{\text{off}}^{\text{beam}}}{2} = \frac{t_{\text{onoff}}}{2n_{\text{beam}}},$$

$$\sigma_{\text{fsw}} = \frac{\sqrt{2} \, n_{\text{beam}} \, T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{d\nu} \, n_{\text{pol}} \, \eta_{\text{tel}} \, t_{\text{tel}}} .$$

$$\frac{A_{\text{map}}}{t_{\text{onoff}}} \leq v_{\text{area}}^{\text{max}}.$$



optimal  $\geq$  von Neumann  $\geq$  cod

WORLDWIDE

$$t_{\text{sig}} = \frac{t_{\text{on}}}{1 + \frac{1}{\sqrt{n_{\text{on/off}}}}} \quad \text{and} \quad \sigma = \frac{T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{d\nu} n_{\text{pol}} t_{\text{on}}} \sqrt{1 + \frac{1}{\sqrt{n_{\text{on/off}}}}}.$$

Alvin Brown

www.fox.com

spiral

www.vivipedia.org







opportunity

$$n_{\text{submap}} = \frac{A_{\text{map}}}{A_{\text{submap}}} \cdot$$

$$n_{\text{on/off}} = \frac{A_{\text{submap}}}{A_{\text{beam}}}.$$

Handwritten text in a cursive script, likely a signature or name, rendered in grayscale. The text is split into three segments by two horizontal lines. The first segment reads "Handwritten", the second segment reads "Text", and the third segment reads "Signature".

Alvin Brown  
—  
Alfred Brown.

Evbbaap=voovt


$$t_{\text{on}}^{\text{beam}} = n_{\text{cover}} t_{\text{on}}^{\text{cover}} \text{ and } t_{\text{off}}^{\text{beam}} = n_{\text{cover}} t_{\text{off}}^{\text{cover}} \text{ with } t_{\text{off}}^{\text{cover}} = \sqrt{n_{\text{on}}/n_{\text{off}}} t_{\text{on}}^{\text{cover}}.$$



$$t_{\text{sig}}^{\text{beam}} = n_{\text{cover}} t_{\text{sig}}^{\text{cover}} = \frac{n_{\text{cover}} t_{\text{submap}}}{n_{\text{on/off}} + \sqrt{n_{\text{on/off}}}}.$$

$$t_{\text{onoff}} = n_{\text{cover}} \text{submap} (n_{\text{on}} / \text{off} t_{\text{on}} + t_{\text{off}} + t_{\text{cover}}).$$

$$t_{\text{onoff}} = n_{\text{cover}} t_{\text{submap}} n_{\text{submap}} \left( 1 + \frac{1}{\sqrt{n_{\text{on/off}}}} \right).$$



$$t_{\text{onoff}} = t_{\text{beam}} \sqrt{\nu_{\text{submap}} \left( 1 + \sqrt{\nu_{\text{onoff}}} \right)^2}.$$

$$t_{\text{onoff}} = t_{\text{sig}} \left( \sqrt{n_{\text{vibmap}}} + \sqrt{n_{\text{beam}}} \right)^2.$$


$$\sigma_{\text{psw}} = \frac{(\sqrt{n_{\text{beam}}} + \sqrt{n_{\text{submap}}}) T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{dv} \eta_{\text{pol}} \eta_{\text{tel}} t_{\text{tel}}} .$$

Adaptation




$$n_{\text{submap}} = \frac{A_{\text{map}}}{v_{\text{area}} t_{\text{submap}}}.$$





www.vivaxip.com



evbvdap v ap v abe v ax  
are




$$t_{\mathrm{sig}}^{\mathrm{beam}} = \frac{T_{\mathrm{sys}}^2}{\eta_{\mathrm{spec}}^2 \sigma^2 dv n_{\mathrm{pol}}},$$





$$t_{\text{onoff}} = t_{\text{sig}} \left( \sqrt{v_{\text{vibrap}}} + \sqrt{v_{\text{beam}}} \right)^2,$$





$$n_{\text{on/off}} = \frac{n_{\text{beam}}}{n_{\text{submap}}},$$

$$n_{\text{cover}} = \frac{t_{\text{sig}}^{\text{beam}}}{t_{\text{submap}}} \left( n_{\text{on/off}} + \sqrt{n_{\text{on/off}}} \right) ,$$

$$t_{\text{on}}^{\text{beam}} = \frac{n_{\text{cover}} t_{\text{submap}}}{n_{\text{on/off}}}$$

beam  
off



beam  
on

beam  
on/off







Answer to the question



$$\sigma_{\text{fsw}} = \frac{\sqrt{2} \, n_{\text{beam}} \, T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{d\nu} \, n_{\text{pol}} \, \eta_{\text{tel}} \, t_{\text{tel}}},$$

$$\sigma_{\text{psw}} = \frac{(\sqrt{n_{\text{beam}}} + \sqrt{n_{\text{submap}}}) T_{\text{sys}}}{\eta_{\text{spec}} \sqrt{dv} \eta_{\text{pol}} \eta_{\text{tel}} t_{\text{tel}}}.$$

$$\frac{\sigma_{\text{psw}}}{\sigma_{\text{fsw}}} = \frac{1}{\sqrt{2}} \left( 1 + \sqrt{\frac{n_{\text{submap}}}{n_{\text{beam}}}} \right) .$$

$$\frac{n_{\text{beam}}}{n_{\text{submap}}} = n_{\text{on/off}} \geq \frac{1}{3 - 2\sqrt{2}} \sim 6.$$




QWERTYUIOPASDFGHJKLZXCVBNM


WORLDWIDE






$$n_{\text{on/off}} = \frac{t_{\text{stable}}}{A_{\text{beam}}/v_{\text{area}}^{\text{max}}},$$















WILL

==

QI

WORLD OF





2460''



VGHS





$$v_{linear}^{max} = f_{dump} \frac{\theta}{4} \text{ arcsec/s}$$

$$v_{\text{area}}^{\text{max}} = f_{\text{dump}} \frac{\theta}{2.5} \frac{\theta}{4} \text{arcsec}^2/\text{s} \quad \text{or} \quad v_{\text{area}}^{\text{max}} = f_{\text{dump}} \frac{\theta^2}{10} \text{arcsec}^2/\text{s}$$





$$t_{\text{onoff}} = t_{\text{on/off}} + t_{\text{off}} = (t_{\text{on/off}} + t_{\text{off}})$$

$$t_{\mathrm{onoff}} = \frac{T_{\mathrm{sys}}^2}{\eta_{\mathrm{spec}}^2 \sigma^2 d\nu} \left( 1 + n_{\mathrm{on/off}} + \alpha + \frac{n_{\mathrm{on/off}}}{\alpha} \right).$$

$$\frac{dt_{\text{on/off}}}{d\alpha}$$

$\propto$

1

—

$$\frac{r_{\text{on/off}}}{\alpha^2}$$

$$\alpha = \sqrt{n_{\text{on/off}}} \text{ or } t_{\text{off}}^{\text{optimal}} = \sqrt{n_{\text{on/off}}} t_{\text{on}}.$$